

LED line PRIME

Code: 471338

EAN: 5907777471338

**RF remote for VARIANTE RGB/RGBW controller**



The RF LED line remote control for the VARIANTE RGB/RGBW controller is an advanced device that allows precise lighting control. It works on 2.4 GHz frequencies, offering a range of up to 20 metres. It is powered by three AAA batteries (included in the set) and its functionality includes the possibility to group controls of as many as four zones and choose from eight dynamic modes and six colours. Additionally, the wall handle provides easy installation.



**Technical data**

Parameter	Value
Warranty	5
Voltage	• 3 V 2*AAA DC
IP protection rating	IP20
Standby power	54
Working power	75
RF frequency	2.4 GHz
RF distance	20
Number of zones	4

Parameter	Value
Standby current	<18
Working current	<25
Ambient temperature suitable for operation	-20÷60
For indoor use	Inside
Length	148 mm
Width	40 mm
Height	20 mm
Weight	0,089 kg


LED line PRIME

Code: 471338

EAN: 5907777471338

**RF remote for VARIANTE RGB/RGBW controller**

**Technical drawing**






**Light distribution**

**Additional product photos**



**Logistics data**



**Single packaging**

Quantity	1
Width	150 mm
Height	36 mm
Length	51 mm
Weight	0,11 kg

**Bulk packaging**

Quantity	100
Width	320 mm
Height	280 mm
Length	380 mm
Volume	0,034 m3
Weight	11,35 kg
Comments	

**Europallet**

Quantity	4000
Height	1,8 m
Quantity in layer	800
Number of layers	5
Bulk quantity	40
Weight	479 kg

---

LED line PRIME

Code: 471338

EAN: 5907777471338

**RF remote for VARIANTE RGB/RGBW  
controller**

---

**Example application**