

LED line PRIME

Code: 471338

EAN: 5907777471338

RF remote for VARIANTE RGB/RGBW controller

The RF LED line remote control for the VARIANTE RGB/RGBW controller is an advanced device that allows precise lighting control. It works on 2.4 GHz frequencies, offering a range of up to 20 metres. It is powered by three AAA batteries (included in the set) and its functionality includes the possibility to group controls of as many as four zones and choose from eight dynamic modes and six colours. Additionally, the wall handle provides easy installation.

**Technical data**





Parameter	Value
Warranty	5
Voltage	• 3 V 2*AAA DC
IP protection rating	IP20
Standby power	54
Working power	75
RF frequency	2.4 GHz
RF distance	20
Number of zones	4

Parameter	Value
Standby current	<18
Working current	<25
Ambient temperature suitable for operation	-20÷60
For indoor use	Inside
Length	148
Width	39
Height	21,2

LED line PRIME

Code: 471338

EAN: 5907777471338

RF remote for VARIANTE RGB/RGBW controller**Technical drawing****Light distribution****Additional product photos****Logistics data****Single packaging**

Quantity	1
Width	148 mm
Height	21,2 mm
Length	39 mm
Weight	0,11 kg

Bulk packaging

Quantity	100
Width	320 mm
Height	280 mm
Length	380 mm
Volume	0,034 m ³
Weight	11,35 kg
Comments	

Europallet

Quantity	4000
Height	1,8 m
Quantity in layer	800
Number of layers	5
Bulk quantity	40
Weight	479 kg

MORE EFFICIENCY FOR THE LED WORLD

LED line

LED line PRIME

Code: 471338

EAN: 5907777471338

**RF remote for VARIANTE RGB/RGBW
controller**

Example application